

Everything you'd expect in a business radio



- 160 ช่อง 245 - 246.9875 MHz
- ลำโพงติดตั้งด้านหน้าเครื่องขนาด 4 วัตต์
- มีปุ่มที่สามารถโปรแกรมฟังก์ชันใช้งานได้ 6 ปุ่ม
- โครงสร้างแข็งแรงระดับมาตรฐานทางทหาร 810F
- มีระบบ 2-Tone 5-Tone CTCSS และ DTCS ในตัว

■ Dependent scan

การโปรแกรมสแกนแบบ dependent การสแกนจะขึ้นอยู่กับช่องใช้งาน เมื่อเปลี่ยนช่องใช้งาน ลิสต์ช่องที่สแกนก็จะเปลี่ยนไปตามลิสต์สำหรับช่องนั้นโดยอัตโนมัติ เมื่อย้ายพื้นที่ใช้งานและเปลี่ยนช่องใช้งานก็ไม่จำเป็นต้องโปรแกรมลิสต์ช่องที่จะสแกนใหม่ ทำให้มีความสะดวกต่อการใช้งาน

■ ปิดการใช้วิทยุ/เปิดใหม่

ฟังก์ชัน stun และ kill สั่งปิดการใช้งานเครื่องที่สัญญาหรือถูกบัง锢โดยไฟทางอากาศ เมื่อเครื่องได้รับคำสั่ง stun ฟังก์ชันทั้งหมดจะถูกล็อกไว้ชั่วคราวจนกว่าจะได้รับคำสั่ง revive หรือใส่ password ปลดล็อก

■ พังก์ชัน TX channel setting และ Talk back

TX channel เป็นช่องที่โปรแกรมให้เป็นช่องส่งในระหว่างสแกน โดยสามารถกำหนดให้ช่องเริ่มนับ ช่องสุดท้ายที่พบสัญญาณ ของ priority หรือช่องไหนได้ เป็นช่องส่ง (TX channel) ได้ หากไม่ได้โปรแกรมช่อง TX channel ไว้ พังก์ชัน Talk back จะจัดช่องสุดท้ายที่พบสัญญาณ เป็นช่องส่ง ในขณะการสแกนยังหยุดรับสัญญาณในช่องนั้นตามเวลาที่กำหนด พังก์ชันนี้ช่วยให้ผู้ใช้วิทยุสามารถตอบกลับได้อย่างรวดเร็ว

■ พังก์ชัน Lone worker

เมื่อเครื่องวิทยุไม่มีการใช้งานในระยะเวลาที่ตั้งไว้ จะมีเสียงบีบและผู้ใช้วิทยุต้องกดปุ่มใช้งานปุ่มใดปุ่มหนึ่ง หากเครื่องวิทยุยังไม่มีการใช้งานภายในระยะเวลาที่ตั้งไว้ เครื่องจะส่งสัญญาณฉุกเฉินอัตโนมัติเป็นการเตือนเพื่อนร่วมงานว่าอาจมีปัญหาเกิดขึ้นกับผู้ใช้วิทยุเครื่องนั้น

■ MDC-1200

- ส่งรหัสเมื่อกดปุ่ม PTT (ส่ง/รับ)
- ฉุกเฉิน ส่ง/รับ (ไม่มี ACK)
- เปิดการใช้วิทยุ (revive)
- Radio check (รับ)
- ปิดการใช้วิทยุ (stun)
- 5 ตารางชื่อจัดตั้ง (สูงสุด)

OTHER FEATURE

- Microphone hanger action programmable
- 8 DTMF autodial memories
- Time-out-timer, Lock-out penalty timer and more

- BIIS 1200 PTT ID transmission
- Power-on password function
- Nuisance delete function

Applicable U.S. Military Specifications

Icom makes rugged products that have been tested to and passed the following MIL-STD requirements and strict environmental standards.

Standard	MIL810 C Method Proc.	MIL810 D Method Proc.	MIL810 E Method Proc.	MIL810 F Method Proc.
Low Pressure	500.1 I	500.2 I, II	500.3 I, II	500.4 I, II
High Temp.	501.1 I	501.2 I, II	501.3 I, II	501.4 I, II
Low Temp.	502.1 I	502.2 I, II	502.3 I, II	502.4 I, II
Temp. Shock	503.1 I	503.2 I	503.3 I	503.4 I
Solar Radiation	505.1 I	505.2 I	505.3 I	505.4 I
Rain Blowing/Dust	506.1 I, II	506.2 I, II	506.3 I, II	506.4 I, II
Humidity	507.1 I, II	507.2 II, III	507.3 II, III	507.4 -
Salt Fog	I	509.2 I	509.3 I	509.4 -
Dust Blowing	509.1 I	510.2 I	510.3 I	510.4 -
Vibration	510.1 I	I	514.4 I	514.5 I
Shock	514.2 VII, X, XI, XII	516.3 I, IV	516.4 I, IV	516.5 I
	516.2 I, II, V, VI	516.3 I, IV	516.4 I, IV	516.5 I, IV

SPECIFICATIONS**GENERAL**

• Frequency range	: 245-246.9875 MHz
• Number of Channels	: 160
• Channel spacing	: 12.5 kHz
• PLL channel step	: 3.125 kHz
• Frequency Stability	: ± 1 ppm
• Antenna impedance	: 50 Ω (SO-239)
• Operating temp. range	: -30°C to 60°C
• Power supply requirement	: 13.6V DC
• Current drain (approx.)	:
Tx 10W	5.5 A
Rx Max. audio	0.7A
Stand-by	250mA
• Dimensions (WxHxD)	: 150×40×167.5 mm
(Projections not included)	
• Weight	: 1.1kg (approx.)

TRANSMITTER

- Output power (at 13.6V DC): 10W/5W/1W
- Max. frequency deviation: ± 2.5kHz
- Frequency error : ± 1ppm
- Spurious emissions : 80 dB
- Adjacent channel power : 60 dB min.
- Audio frequency response :

 - +1dB to -3dB of +6dB/octave with 300-3000Hz

- FM Hum and Noise : 45 dB
- Residual modulation : 50 dB (With CCITT filter)
- Audio harmonic distortion : 3% (40% deviation)
- Modulation limiting : 70-100% of Max. deviation
- External Mic. impedance : 600Ω (8-pin modular)

RECEIVER

- Sensitivity : 0.25μV (at 12 dB SINAD)
- Squelch sensitivity : 0.25μV (at threshold)
- Adjacent Ch. selectivity : 60dB
- Spurious response : 80 dB
- Intermodulation : 75 dB
- Hum and noise ratio : 45 dB
- Audio output power : 4W at 3% distortion
- External SP connector : 2-conductor 3.5 (d) mm (1/8")/4Ω

Supplied Accessories

- Hand mic. (HM-239T)
- DC power cable
- Mounting bracket kit
- Microphone hanger
- Key assign stickers

All stated specifications are subject to change without notice or obligation.

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

HAND MICROPHONES

HM-152 : Regular hand microphone.

HM-239T : DTMF microphone. Same as supplied.

HM-148G: Heavy duty microphone. Self-grounding type.

HM-148T : Heavy duty microphone with DTMF keypad. Self-grounding type.

DESKTOP MICROPHONE SM-26

Convenient for dispatching, equipped with monitor switch.

ACC CABLE OPC-1939

15-pin ACC cable. For connecting with a PC, external speaker, external channel control, ignition sense line or vehicle's horn.

Icom and the Icom logo are registered trademarks of Icom Incorporated (Japan) in Thailand.

Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

Count on us!

Icom America Inc.

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone: +1 (425) 454-8155
Fax : +1 (425) 454-1509
E-mail : sales@icomamerica.com
URL : <http://www.icomamerica.com>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone : +64 (09) 274 4062
Fax : +64 (09) 274 4708
E-mail : inquiries@icom.co.nz
URL : <http://www.icom.co.nz>

Icom (UK) Ltd.

Blacksole House, Altira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone : +44 (01227) 741741
Fax : +44 (01227) 741742
E-mail : info@icomuk.co.uk
URL : <http://www.icomuk.co.uk>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone : +886 (02) 2559 1899
Fax : +886 (02) 2559 1874
E-mail : sales@asia-icom.com
URL : <http://www.asia-icom.com>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindejonc des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone : +33 (5) 61 36 03 03
Fax : +33 (5) 61 36 03 00
E-mail : icom@icom-france.com
URL : <http://www.icom-france.com>

Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88,
Yong Ding Road, Haidian District,
Beijing, 100039, China
Phone : +86 (010) 5889 5391/5392/5393
Fax : +86 (010) 5889 5395
E-mail : bjicom@bjicom.com
URL : <http://www.bjicom.com>

Icom Polska

81-850 Sopot, ul. 3 Maj 54, Poland
Phone : +48 (58) 550 7135
Fax : +48 (58) 551 0484
E-mail : icompoliska@icompoliska.com.pl
URL : <http://www.icompoliska.com.pl>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone : +61 (03) 9549 7500
Fax : +61 (03) 9549 7505
E-mail : sales@icom.net.au
URL : <http://www.icom.net.au>

Icom Spain S.L.

Ctra. Rubí, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Vallès,
Barcelona, Spain
Phone : +34 (93) 590 26 70
Fax : +34 (93) 589 04 46
E-mail : icom@icomspain.com
URL : <http://www.icomspain.com>

บีซี อะเมเจอร์ กรุ๊ป จำกัด

10/5-9-11 หมู่ 4 ถนนพุกเบื้อ ตำบลรักน้อย อ.เมืองสระบุรี จ.สระบุรี 11000

Tel : 02-150-9555

ID Line : @amg789

